

# SPECIFICATIONS FOR LCD MODULE

CUSTOMER	
CUSTOMER PART NO.	
AMPIRE PART NO.	AM-1024768ATZQW-31
APPROVED BY	
DATE	

□Approved For Specifications

□ Approved For Specifications & Sample

APPROVED BY	CHECKED BY	ORGANIZED BY

Date . $2019/02/23$	Date :	2019/02/25
---------------------	--------	------------

AMPIRE CO., LTD.

Marelcom AG

1

## RECORD OF REVISION

Revision Date	Page	Contents	Editor
2019/02/25		New Release	Mark

#### **1.0 General Descriptions**

#### **1.1 Introduction**

AM-1024768ATZQW-31 is a 15.0" TFT Liquid Crystal Display IAV module with LED Backlight units and HDMI interface. This module supports 1024 x 768 XGA mode and can display 16.2M/262k colors.

The PSWG is to establish a set of displays with standard mechanical dimensions and select electrical interface requirements for an industry standard 15.0" XGA LCD panel and the LED driving device for Backlight is built in PCBA.

#### 1.2 Features

- XGA (1024 x 768 pixels) resolution
- HDMI Interface
- PSWG (Panel Standardization Working Group)
- Wide operating temperature.
- RoHS compliance
- -LCM connect to HDMI Board J1 connector

#### 1.4 General specifications

Items	Specifications	Unit	Note
Active Area	304.1 (H) x 228.1(V) (15.0" diagonal)	mm	
Bezel Opening Area	307.4(H) x 231.3(V)	mm	
Driver Element	a-Si TFT active matrix	-	
Pixel Number	1024 x R.G.B x 768	Pixel	
Pixel Pitch	0.297(H) x 0.297(W)	mm	
Pixel Arrangement	RGB vertical Stripe		
Display Colors	16.2M / 262K	Color	
Display Mode	Normally Black	-	
Surface Treatment	Hard Coating (3H), Anti-Glare	-	

ltem		Min.	Тур.	Max	Unit	Note
	Horizontal(H)	326	326.5	327	mm	(1)
Module Size	Vertical(V)	253	253.5	254	mm	(1)(2)
	Depth(D)	8.6	9.1	9.6	mm	
DerelAree	Horizontal	307.1	307.4	307.7	mm	
Dezel Alea	Vertical	231	231.3	231.6	mm	
Activo Aroa	Horizontal	-	304.1	-	mm	
Active Area	Vertical	-	-	-	mm	

#### 1.5 Mechanical specifications

Note (1) Please refer to the attached drawings for more information of front and back outline dimensions.

Note (2) The depth is without connector.



#### 2.0 Absolute Maximum Ratings

# For Design reference only. These supply voltage and signals do not need to input by end user

#### 2.1 ABSOLUTE RATINGS OF ENVIRONMENT

Item	Symbol	Min	Max	Unit	Note
Operating Ambient Temperature	T <sub>OP</sub>	-20	+70	°C	(1)(2)(3)
Storage Temperature	T <sub>ST</sub>	-30	+70	°C	(1)(2)(3)

Note (1) Temperature and relative humidity range is shown in the figure below.

(2) 90 %RH Max. (Ta < 40°C).

(3) Wet-bulb temperature should be 39°C Max.



#### 2.2 ELECTRICAL ABSOLUTE RATINGS

#### 2.2.1 TFT LCD MODULE

Item	Symbol	Min	Max	Unit	Note
Power Supply Voltage	V <sub>CC</sub>	-0.3	4	V	(1)

Item	Symbol	Min	Max	Unit	Note
Converter Voltage	Vi	-0.3	18	V	(1)(2)
Enable Voltage	EN	-	5.5	V	

Note (1) Permanent damage to the device may occur if maximum values are exceeded. Function operation should be restricted to the conditions described under Normal Operating Conditions. Note (2) Specified values are for lamp (Refer to 3.2 for further information).

#### **3. ELECTRICAL CHARACTERISTICS**

# For Design reference only. These supply voltage and signals do not need to input by end user

#### 3.1 TFT LCD MODULE

Itom	Item	Symbol		Value			Noto
Item		Symbol	Min.	Тур.	Max	Unit	NOLE
Power Supply Voltage	V <sub>CC</sub>	3.0	3.3	3.6	V	-	
Ripple Voltage		V <sub>RIP</sub>	I	-	100	mVp-p	(2)
Rush Current		I <sub>RUSH</sub>	I	-	2.0	A	(3)a
Power Supply Current	White	I <sub>CC</sub>	I	800	960	mA	(3)b
	Black		-	670	800	mA	
LVDS differential input voltage		V <sub>id</sub>	200	-	600	mV	
LVDS common input voltage		V <sub>ic</sub>	1.0	1.2	1.4	V	
Differential Input Voltage for	"H" level	VIH	-	-	100	mV	
LVDS Receiver Threshold	"L" level	V <sub>IL</sub>	-100	-	-	mV	
Terminating Resistor		R <sub>T</sub>	-	100	-	ohm	

Note (1) The module should be always operated within above ranges.

Note (2) Measurement Conditions:





Note (3) The specified power supply current is under the conditions at  $V_{DD}$  =3.3V, Ta = 25 ± 2 °C, DC Current and  $f_v$  = 60 Hz, whereas a power dissipation check pattern below is displayed.

a. White Pattern

b. Black Pattern



Active Area



Active Area

#### **3.2 BACKLIGHT UNIT**

# For Design reference only. These supply voltage and signals do not need to input by end user

ITEM	SYMBOL	MIN	TYP	MAX	UNIT	CONDITION
LED Backlight Voltage	$V_BL$	-	24.5	1	V	For reference
LED Backlight Current	I <sub>BL</sub>	-	360		mA	Ta=25°C
LED Life Time			50K	-	KHr	Note*

Note\* : Brightness to be decreased to 50% of the initial value. Ta=25 $^\circ\!\mathrm{C}$ 



When LCM is operated over  $40^\circ\!\mathrm{C}\,$  ambient temperature, the ILED should be follow :



### 4. BLOCK DIAGRAM 4.1 TFT LCD MODULE



#### 5. INPUT TERMINAL PIN ASSIGNMENT

#### 5.1 TFT LCD MODULE

Pin No.	Symbol	Function	Polarity	Note
1	VCC	Power Supply +3.3V(typical)		
2	VCC	Power Supply +3.3V(typical)		
3	NC	No Connection (Reserve for INX test)		
		Reverse Scan Control,		
4	LR/UD	High level or NC = Normal Mode.		
		Level = Horizontal/ Vertical Reverse Scan.		
5	RX0-	LVDS Differential Data Input	Negative	
6	RX0+	LVDS Differential Data Input	Positive	
7	GND	GND		
8	RX1-	LVDS Differential Data Input	Negative	
9	RX1+	LVDS Differential Data Input	Positive	
10	NC	No Connection (Reserve for INX test)		
11	RX2-	LVDS Differential Clock Input	Negative	
12	RX2+	LVDS Differential Clock Input	Positive	
13	GND	GND		
14	RXCLK-	LVDS Differential Data Input	Negative	
15	RXCLK+	LVDS Differential Data Input	Positive	
16	GND	GND		
17	RX3-	LVDS Differential Data Input	Negative	
18	RX3+	LVDS Differential Data Input	Positive	
19	NC	No Connection (Reserve for INX test)		
		LVDS 6/8 bit select function control,		
20	SEL68	High level: 6bit Input Mode.		Note(3)
		Low level or NC: 8bit Input Mode.		

Note (1) Connector Part No.: Cvilux CID520D1HR0-NH or equivalent.

Note (2) User's connector Part No.: Hirose DF14-20S-1.25C or equivalent.

Note (3) "Low" stands for 0V. "High" stands for 3.3V. "NC" stands for "No Connection".

#### LR/UD Pin

Panel Board





#### 5.3 COLOR DATA INPUT ASSIGNMENT

The brightness of each primary color (red, green and blue) is based on the 8-bit gray scale data input for the color. The higher the binary input the brighter the color. The table below provides the assignment of color versus data input.

		1										D	ata	Sig	nal										
	Color				R	ed							Gre	een							BI	ue			
		R7	R6	R5	R4	R3	R2	R1	R0	G7	G6	G5	G4	G3	G2	G1	G0	B7	B6	B5	B4	B3	B2	B1	BO
	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
10 T	Green	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
Basic	Blue	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
Colors	Cyan	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	Magenta	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
	Yellow	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	White	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	Red(0) / Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(1)	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Crow	Red(2)	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Gray	:	:	:	:	100	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
Of	:	:	:	:	1	:	:	:	:	:	:	1	:	:	:	:	:	:	:	:	:	1	:	:	:
Dod	Red(252)	1	1	1	1	1	1	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Reu	Red(252)	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(252)	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green(0)/Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green(1)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0
Cray	Green(2)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0
Scala	:	:	:	:	12	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	1	:	:	:
Of	:	:	:	:		:	;	:	:	:	:	:	1	:	ः	3	:	:	:	:	:	1	:	:	:
Groon	Green(252)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	0	1	0	0	0	0	0	0	0	0
Green	Green(252)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0
	Green(252)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	Blue(0) / Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Blue(1)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
Grav	Blue(2)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0
Scale	:	3	:	1		:	1	:	:	:	3	1	2	:	<u>i</u>	5		- 20	:	0	:	1	:	:	:
Of	:	:	:	:	1	:	:	:	:	:	1	:	:	:	:	:	:	:	:	:	:	1	:	3	:
Blue	Blue(252)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	0	1
Dide	Blue(252)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0
	Blue(252)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1

Note (1) 0: Low Level Voltage, 1: High Level Voltage

#### 6. INTERFACE TIMING

# For Design reference only. These supply voltage and signals do not need to input by end user

#### **6.1 INPUT SIGNAL TIMING SPECIFICATIONS**

	0 1		0				
Signal	ltem	Symbol	Min	Min	Max	Unit	Note
	Frequency	Fc	53.35	65	80	MHz	
	Period	Tc	12.5	15.38	18.75	Ns	
	Input cycle to cycle jitter	T <sub>rcl</sub>	-	-	200	Ns	(a)
LVDS Clock	Input Clock to data skew	TLVDS	02*Tc	-	0.02*Tc	Ps	(b)
	Spread spectrum modulation range	F <sub>clkin_mod</sub>	-	-	1.02*Fc	MHz	
	Spread spectrum modulation frequency	F <sub>SSM</sub>	-	-	200	KHz	(0)
	Frame Rate	Fr	55	60	70	Hz	Tv=Tvd+Tvb
Vertical	Total	Τv	780	806	840	Th	-
Display Term	Active Display	T <sub>vd</sub>	768	768	768	Th	-
	Blank	T <sub>vb</sub>	Tv-Tvd	38	Tv-Tvd	Th	-
Llevimentel	Total	T <sub>h</sub>	1240	1344	1360	Тс	Th=Thd+Thb
Horizontal	Active Display	T <sub>hd</sub>	1024	1024	1024	Tc	-
	Blank	T <sub>hb</sub>	Th-Thd	320	Th-Thd	Tc	-

The input signal timing specifications are shown as the following table and timing diagram.

Note (1) Because this module is operated by DE only mode, Hsync and Vsync input signals should be set to low logic level or ground. Otherwise, this module would operate abnormally.

Note (2) The Tv(Tvd+Tvb) must be integer, otherwise, the module would operate abnormally.

#### INPUT SIGNAL TIMING DIAGRAM



#### TIMING DIAGRAM of LVDS



Note (a) The input clock cycle-to-cycle jitter is defined as below figures. Trcl = I T1 - TI



Note (b) Input Clock to data skew is defined as below figures.



Note (c) The SSCG (Spread spectrum clock generator) is defined as below figures.



#### 6.2 POWER ON/OFF SEQUENCE

To prevent a latch-up or DC operation of LCD assembly, the power on/off sequence should be as the diagram below.



#### Power ON/OFF sequence

Note (1) Please avoid floating state of interface signal at invalid period.

Note (2) When the interface signal is invalid, be sure to pull down the power supply of LCD VCC to 0 V.

Note (3) The Backlight converter power must be turned on after the power supply for the logic and the interface signal is valid. The Backlight converter power must be turned off before the power supply for the logic and the interface signal is invalid.

Daramotor		Value		Unite
Farameter	Min	Тур	Max	Units
T1	0.5	-	10	ms
T2	0	-	50	ms
Т3	0	-	50	ms
Τ4	500	-	-	ms
Τ5	200	-	-	ms
Т6	200	-	-	ms
Τ7	5	-	300	ms
Т8	10	-	-	ms
Т9	10	_	-	ms
T10	20		50	ms

#### **6.3 SCANNING DIRECTION**

The following figures show the image see from the front view. The arrow indicates the direction of scan.

#### Fig.1 Normal Scan



Fig. 1 Normal scan (pin 4, LR/UD = High or NC)

Fig. 2 Reverse scan (pin 4, LR/UD = Low)

#### Fig.2 Reverse Scan



#### 7. OPTICAL CHARACTERISTICS

#### 7.1 TEST CONDITIONS

Item	Value	Unit	
Ambient Temperature (Ta)	25±2	So	
Ambient Humidity (Ha)	50±2	%RH	
Supply Voltage			
Input Signal			
LED Light Bar Input Current Per Input Pin	CHARACTE	Nonco	

#### 7.2 OPTICAL SPECIFICATIONS

The relative measurement methods of optical characteristics are shown in 7.2 and all items are measured at the center point of screen except white variation. The following items should be measured under the test conditions described in 7.1 and stable environment shown in Note (5).

Item		Symbol	Conditions	Min.	Тур.	Max.	Unit	Note
	Red	Rx	-		TBD			
	Red	Ry	-		TBD			(1) (5)
	Green	Gx	-		TBD			
Color	Green	Gy			TBD		-	
Chromaticity	Blue	Bx	$\theta_X = \theta_Y = 0$		TBD	-	-	(1),(0)
	Bide	Ву	BM-7/		TBD			
	White	Wx	CS-1000T		TBD			
	VIIIto	Wy			TBD			
Center Luminance of White		LC		400	500		cd/m <sup>2</sup>	(4),(5)
Contrast Ratio		CR		1300	2000		-	(2),(5)
Deenenee Time			0 -0 -0°	-	16	21		(2)
Response Time		TF	0 <sub>X</sub> -0 <sub>Y</sub> -0	-	7	14	ms	(3)
White Variation		δW	$\theta_X = \theta_Y = 0^{\circ}$	-	1.25	1.33	-	(5),(6)
	Horizoptol	$\theta_{X^+}$		80	88	-		
Viewing Angle	Horizontai	θ <sub>x-</sub>		80	88	-	Dog	(1),(5)
	Vortical	$\theta_{Y^+}$		80	88	-	Dey.	
	venical	θ <sub>Y-</sub>		80	88	-		

Note (1) Definition of Viewing Angle  $(\theta_X, \theta_Y)$ :



Note (2) Definition of Contrast Ratio (CR):

The contrast ratio can be calculated by the following expression.

Contrast Ratio (CR) = L255 / L0

L255: Luminance of gray level 255

L0: Luminance of gray level 0

CR = CR(5)

CR (X) is corresponding to the Contrast Ratio of the point X at Figure in Note (6).

Note (3) Definition of Response Time (TR, TF):



Note (4) Definition of Luminance of White (Lc):

Measure the luminance of gray level 255 at center point

Lc = L (5)

L (x) is corresponding to the luminance of the point X at Figure in Note (6).

Note (5) Measurement Setup:

The LCD module should be stabilized at given temperature for 20 minutes to avoid abrupt temperature change during measuring. In order to stabilize the luminance, the measurement should be executed after lighting Backlight for 20 minutes in a windless room.



Note (6) Definition of White Variation ( $\delta W$ ):

Measure the luminance of gray level 63 (255) at 9 points



#### 8. RELIABILITY TEST CRITERIA

Test Item	Test Condition	Note	
High Temperature Storage Test	70°C, 240 hours	(1),(2),(3),(4)	
Low Temperature Storage Test	-30°C, 240 hours		
Thermal Shock Storage Test	-30°C, 0.5 hour←→70°C, 0.5 hour; 100cycles, 1 hour/cycle)		
High Temperature Operation Test	70°C, 240 hours		
Low Temperature Operation Test	-20°C, 240 hours		
High Temperature & High Humidity Operation Test	60°C, RH 90%, 240 hours	(1),(2),(3),(5)	

Note (1) There should be no condensation on the surface of panel during test.

Note (2) Temperature of panel display surface area should be 73°C Max.

Note (3) In the standard conditions, there is no function failure issue occurred. All the cosmetic

specification is judged before reliability test.

Note (4) Before cosmetic and function test, the product must have enough recovery time, at least 2 hours at room temperature.

Note (5) Before cosmetic and function test, the product must have enough recovery time, at least 24 hours at room temperature.

#### **9 USE PRECAUTIONS**

#### 9.1 Handling precautions

- 1) The polarizing plate may break easily so be careful when handling it. Do not touch, press or rub it with a hard-material tool like tweezers.
- 2) Do not touch the polarizing plate surface with bare hands so as not to make it dirty. If the surface or other related part of the polarizing plate is dirty, soak a soft cotton cloth or chamois leather in benzine and wipe off with it. Do not use chemical liquids such as acetone, toluene and isopropyl alcohol. Failure to do so may bring chemical reaction phenomena and deteriorations.
- 3) Remove any spit or water immediately. If it is left for hours, the suffered part may deform or decolorize.
- 4) If the LCD element breaks and any LC stuff leaks, do not suck or lick it. Also if LC stuff is stuck on your skin or clothing, wash thoroughly with soap and water immediately.

#### 9.2 Installing precautions

- 1) The PCB has many ICs that may be damaged easily by static electricity. To prevent breaking by static electricity from the human body and clothing, earth the human body properly using the high resistance and discharge static electricity during the operation. In this case, however, the resistance value should be approx.  $1M\Omega$  and the resistance should be placed near the human body rather than the ground surface. When the indoor space is dry, static electricity may occur easily so be careful. We recommend the indoor space should be kept with humidity of 60% or more. When a soldering iron or other similar tool is used for assembly, be sure to earth it.
- 2) When installing the module and ICs, do not bend or twist them. Failure to do so may crack LC element and cause circuit failure.
- 3) To protect LC element, especially polarizing plate, use a transparent protective plate (e.g., acrylic plate, glass etc) for the product case.
- 4) Do not use an adhesive like a both-side adhesive tape to make LCD surface (polarizing plate) and product case stick together. Failure to do so may cause the polarizing plate to peel off.

#### 9.3 Storage precautions

- 1) Avoid a high temperature and humidity area. Keep the temperature between 0°C and 35°C and also the humidity under 60%.
- 2) Choose the dark spaces where the product is not exposed to direct sunlight or fluorescent light.
- 3) Store the products as they are put in the boxes provided from us or in the same conditions as we recommend.

#### 9.4 Operating precautions

- 1) Do not boost the applied drive voltage abnormally. Failure to do so may break ICs. When applying power voltage, check the electrical features beforehand and be careful. Always turn off the power to the LC module controller before removing or inserting the LC module input connector. If the input connector is removed or inserted while the power is turned on, the LC module internal circuit may break.
- 2) The display response may be late if the operating temperature is under the normal standard, and the display may be out of order if it is above the normal standard. But this is not a failure; this will be restored if it is within the normal standard.
- 3) The LCD contrast varies depending on the visual angle, ambient temperature, power voltage etc. Obtain the optimum contrast by adjusting the LC dive voltage.
- 4) When carrying out the test, do not take the module out of the low-temperature space suddenly. Failure to do so will cause the module condensing, leading to malfunctions.
- 5) Make certain that each signal noise level is within the standard (L level: 0.2Vdd or less and H level: 0.8Vdd or more) even if the module has functioned properly. If it is beyond the standard, the module may often malfunction. In addition, always connect the module when making noise level measurements.
- 6) The CMOS ICs are incorporated in the module and the pull-up and pull-down function is not adopted for the input so avoid putting the input signal open while the power is ON.

- 7) The characteristic of the semiconductor element changes when it is exposed to light emissions, therefore ICs on the LCD may malfunction if they receive light emissions. To prevent these malfunctions, design and assemble ICs so that they are shielded from light emissions.
- 8) Crosstalk occurs because of characteristics of the LCD. In general, crosstalk occurs when the regularized display is maintained. Also, crosstalk is affected by the LC drive voltage. Design the contents of the display, considering crosstalk.

#### 9.5 Other

- 1) Do not disassemble or take the LC module into pieces. The LC modules once disassembled or taken into pieces are not the guarantee articles.
- 2) Do not keep the LCD at the same display pattern continually. The residual image will happen and it will damage the LCD. Please use screen saver.
- 3) AMIPRE will provide one year warrantee for all products and three months warrantee for all repairing products.

#### **10. MECHANIC DRAWING**







晶采光電科技股份有限公司 AMPIRE CO., LTD.

# Auxiliary

# AMPIRE HDMI Board REV.D

AMPIRE CO., LTD. Building A., 4F., No.116, Sec. 1, Sintai 5th Rd., Xizhi Dist, New Taipei City 221, Taiwan (R.O.C.) 新北市汐止區新台五路一段 116 號 4 樓(東方科學園區 A 棟) TEL:886-2-26967269, FAX:886-2-26967196 or 26967270

## **RECORD OF REVISION**

Revision Date	Page	Contents	Editor
2018/06/19	-	New Release	Mark

# 1. Features

HDMI to LCD interface board

- Single Power input: 12V / 2A power input. (Connector: PJ1 or PJ2).
- LCD LVDS output: 24 BIT Single LVDS
- HDMI Digital input : (Connector: HDMI1)
  - ♦ HDMI 1.4a Compliant
  - Single-link (Type A HDMI) on-chip TMDS receiver up to 225MHz. Support long cable.
  - Do not support HDCP.



# 2. Support input video format :

Resolution	V Sync	Resolution	V Sync
640x480	60	1280x800	60
640x480	72	1280x800	75
640x480	75	1280x960	60
800x600	56	1280x1024	60
800x600	60	1280x1024	75
800x600	72	1360x768	60
800x600	75	1366x768	60
848x480	60	1400x1050	60
1024x768	60	1400x1050	75
1024x768	70	1440x900	60
1024x768	75	1440x900	75
1152x864	75	1600x900	60
1280x720	60	1680x1050	60
1280x768	60	1680x1050	75
1280x768	75	1920x1080	60

## **3. CONNECTOR**

# 3.1 POWER CONNECTOR (PJ1 \ PJ2)

PIN	Symbol	Description
1	+12V	POWER SUPPLY +12V
3	GND	POWER SUPPLY GROUND



# 3.2 J1\_20PIN LVDS

Pin No.	Symbol	Function
1	VDD	POWER SUPPLY:3.3V
2	VDD	POWER SUPPLY:3.3V
3	GND	Power Ground
4	GND	Power Ground
5	IN0-	Transmission Data of Pixels
6	IN0+	Transmission Data of Pixels
7	GND	Power Ground
8	IN1-	Transmission Data of Pixels 1
9	IN1+	Transmission Data of Pixels 1
10	GND	Power Ground
11	IN2-	Transmission Data of Pixels 2
12	IN2+	Transmission Data of Pixels 2
13	GND	Power Ground
14	CLK-	Sampling Clock
15	CLK+	Sampling Clock
16	GND	Power Ground
17	JUMP	JUMP
18	JUMP	JUMP
19	GND	Power Ground
20	JUMP	JUMP



# 3.3 J2\_40PIN LVDS

Pin #	Singnal Name	Description	Remarks
1	NC	Not Connect	-
2	VDD	Power Supply, 3.3V (typical)	-
3	VDD	Power Supply, 3.3V (typical)	
4	NC	Not Connect	
5	NC	Not Connect	
6	NC	Not Connect	
7	NC	Not Connect	
8	LV0N	-LVDS differential data input	
9	LV0P	+LVDS differential data input	
10	GND	Ground	
11	LV1N	-LVDS differential data input	
12	LV1P	+LVDS differential data input	
13	GND	Ground	
14	LV2N	-LVDS differential data input	
15	LV2P	+LVDS differential data input	
16	GND	Ground	
17	LVCLKN	-LVDS differential data input	
18	LVCLKP	+LVDS differential data input	
19	GND	Ground	
20	LV3N	-LVDS differential data input	
21	LV3P	+LVDS differential data input	
22	GND	Ground	
23	LED_GND	Ground for LED Driving	
24	LED_GND	Ground for LED Driving	
25	LED_GND	Ground for LED Driving	
26	NC	Not Connect	
27	LED_PWM	PWM Input signal for LED driver	
28	LED_EN	LED Enable Pin	
29	Not Connect	NC	
30	NC	Not Connect	
31	LED_VCC	Power Supply for LED Driver	
32	LED_VCC	Power Supply for LED Driver	
33	LED_VCC	Power Supply for LED Driver	
34	NC	Not Connect	
35	BIST	BIST pin	
36-40	NC	Not Connect	



### JUMP FOR PIN17 to PIN20 and VLED

- These jump only for J1\_20PLVDS
- For Design reference only. These supply voltage and signals do not need to input by end user.



# 3.4 J3 40PIN LVDS

Pin #	Singnal Name	Description	Remarks
1	VDD	Power Supply, 3.3V (typical)	-
2	VDD	Power Supply, 3.3V (typical)	-
3	VDD	Power Supply, 3.3V (typical)	
4	VDD	Power Supply, 3.3V (typical)	
5	VDD	Power Supply, 3.3V (typical)	
6	VDD	Power Supply, 3.3V (typical)	
7	NC	Not Connect	
8	NC	Not Connect	
9	GND	Ground	
10	GND	Ground	
11	LV8N	-LVDS differential data input	
12	LV5N	-LVDS differential data input	
13	LV8P	+LVDS differential data input	
14	LV5P	+LVDS differential data input	
15	GND	Ground	
16	GND	Ground	
17	LVCLK1N	-LVDS differential data input	
18	LV6N	-LVDS differential data input	
19	LVCLK1P	+LVDS differential data input	
20	LV6P	+LVDS differential data input	
21	GND	Ground	
22	GND	Ground	
23	LV0N	-LVDS differential data input	
24	LV7N	-LVDS differential data input	
25	LV0P	+LVDS differential data input	
26	LV7P	+LVDS differential data input	
27	GND	Ground	
28	GND	Ground	
29	LV1N	-LVDS differential data input	
30	LV3N	-LVDS differential data input	
31	LV3P	+LVDS differential data input	
32	LV7P	+LVDS differential data input	
33	GND	Ground	
34	GND	Ground	
35	LV2N	-LVDS differential data input	
36	LVCLK0N	-LVDS differential data input	
37	LV2P	+LVDS differential data input	
38	LVCLK0P	+LVDS differential data input	
39	GND	Ground	
40	GND	Ground	



0.0	04 Duck	-igin			
Pin No.	Symbol	I/O	Description	Note	
1	VLED	Р	Voltage for LED circuit (5.0V or 12V)		
2	GND	I	Power ground		
3	ADJ	Р	Adjust the LED brightness by PWM		
4	LED_EN	I	LED BLU ON/OFF. High level: ON; Low level: OFF.		





# 3.6 BackLight A,K Connector

•	Only	/ for	external	backlig	ıht	connector
-			ontornar	Subing		0011100101

Pin No.	Symbol	Description
1	А	Anode
2	K	Cathode



- 3.7 JP6 Keypad connector for HDMI Board
- Optional item
- If customer need, please check with Ampire sales for new part no. and sample.



## 4. INTERFACE PIN CONNECTION INTERFACE (HDMI Interface Board)

#### • PJ1 & PJ2 Power Supply Power Jack:

Inner terminal is positive. Outer terminal is GND



# HDMI1: HDMI Type A Connector

НОМІ						
1 3 19 Full see 2 4 18						
PIN	SIGNAL	PIN	SIGNAL			
1	TMDS Data2+	11	TMDS Clock Shield (Ground)			
2	TMDS Data2 Shield (Ground)	12	TMDS Clock-			
3	TMDS Data2-	13	CEC (not used)			
4	TMDS Data1+	14	Reserved (No Connection)			
5	TMDS Data1 Shield (Ground)	15	SCL			
6	TMDS Data1-	16	SDA			
7	TMDS Data0+	17	DDC/CED (Ground)			
8	TMDS Data0 Shield (Ground)	18	+5V input			
9	TMDS Data0-	19	Hot Plug Detect			
10	TMDS Clock+					

# 5. Outline Dimension



